Motorola A1200
WAP, MMS and IMAP4 Email Service Setup Guide

All Motorola A1200 purchased from CSL outlets are already programmed with the standard setting of @1010 or One2Free Zone. Should you wish to make a new setting or lose your original one in any circumstances, please follow the procedures below. This service allows you to access in Hong Kong or overseas. When you access the service from overseas, roaming charges will be incurred.

(I)   Setup for Standard Local and Overseas WAP services

1. Tap " 🔲 " enter main menu and according to the following step to select "Setup" → "Data Network" → Select profile to be edited → " 🔳 " → "Edit" → input the following parameters in table.

Services		GPRS / CSD (local)	CSD (Overseas) only
Profile name		CSL	CSL CSD Overseas
GPRS setting	**APN**	hkcsl	Leave it blank
	User name	Leave it blank	
	Password	Leave it blank	
	Timeout	15 min	Off
	Primary gateway IP	192.168.59.51	
	Port	8080	
	Secondary gateway IP	Leave it blank	
	Port	0	
DNS server		☐	
	(**1**)	Leave it blank	
	(**2**)	Leave it blank	
CSD Setting	**Dial in number**	179111	+852179112
	Query at Logon	☐	
	User name	Leave it blank	
	Password	Leave it blank	
	Baud rate	9600	
	Line type	ISDN	Modem
	Timeout	5 min	
DNS server		☐	
	(**1**)	Leave it blank	
	(**2**)	Leave it blank	

2. When completed, tap "Save" then " 🔲 " back to main menu. .
3. Tap " 🔲 " → "Browser" icon → " 🔳 " → "Setup" → "Profiles" → select any one of the profiles → " 🔳 "→ "Edit" → input the following parameters in table.

Profile name	(1010 customer)	@1010	1010 Overseas CSD
	(One2Free customer)	One2Free Zone	O2F Overseas CSD
Homepage:	(1010 customer)	http://wap.hkcsl.com/1010/	
	(One2Free customer)	http://wap.hkcsl.com/o2f/	
Network link		CSL	CSL CSD Overseas

4. When complete, tap "Save" → " 🔲 " → select the profile as default (e.g.: @1010 or One2Free Zone) → "Save" → tap " 🔲 " to quit.

Note: For switching the data connection from CSD to GPRS in WAP browsing, the user requires to exit the WAP browser and re-enters again while GPRS is in coverage.

(II)   Setup for Multimedia Messaging Service (MMS)

1. Tap " 🔡 " enter main menu and according to the following step to select "Setup" → "Data Network" → Select profile to be edited → " 🗐 " → "Edit" → input the following parameters in table.

Profile name		CSL MMS
GPRS setting	**APN**	hkcsl
	User name	Leave it blank
	Password	Leave it blank
	Timeout	15 min
	Primary gateway IP	192.168.59.51
	Port	9201
	Secondary gateway IP	Leave it blank
	Port	0
DNS server		☐
	(1)	Leave it blank
	(2)	Leave it blank
CSD Setting		Leave it blank
DNS server		☐
	(1)	Leave it blank
	(2)	Leave it blank

2. When completed, tap "Save" then " ↵ " back to main menu.
3. Tap " ✉ " → " 🗐 " → "Service Setup" → "Multimedia Message" → input the following parameters in table:

Default Profile	**Profile name**	CSL MMS
Tap " 🗂 " → Tap " 🗐 "	**MMSC**	http://192.168.58.171:8002
→ "New" or "Edit"	**Max Sending Size**	100K
	Network Profile	CSL MMS
Tap "Save" → recall the profile "CSL MMS" → "Set as Default"		
Expire After	Maximum	
Auto Download	☑	
not when roaming	☑	
not if more than	☐	
Show My Number	☑	
Allow Delivery Report	☐	
Blocked Sender(s)	Leave it blank	
Reject read reply request	☑	
Auto Retry	☐	

4. When complete. Tap "Save" → Tap " ↵ " to Exit

(III) Setup for IMAP4 Email Account

Setting in part I must be created before.

1. Tap "" enter main menu and according to following step to select "Email" icon → "" → "Mailbox Setup" → "New" → Tap "Setup Manually" → "OK" → input the following parameters in table:

Mailbox Name		Mail@1010 (1010 customer)	O2F Email (One2Free customer)
Send Setup	**Server**	mail.csl1010.com	mail.one2free.com
	Port	25	
	Email	xxxxxxxx@csl1010.com	xxxxxxxx@one2free.com
		Where xxxxxxxx is your mobile phone number	
	Nickname	(User define)	
	Authentication	⊙ Off	
	Same as Receive Setup	☑	
	Use SSL	⊙ No	
Receive Setup		IMAP	
	Server	imap.csl1010.com	imap.one2free.com
	Port	143	
	User Name	xxxxxxxx (Your mobile phone number)	
	Password	xxxxxx (User define)	
	Re-enter Password	xxxxxx (Same as user define)	
	Check All Folders	☐	
	Save Special Folder	☐	
	Incoming Message Size Limit	64K	
	Use SSL	⊙ No	
Signature Setup	**Add signature to all outgoing massages**	☐	
Connection Setup	**Profile**	CSL	

2. When complete, tap "OK" → "" → Tap "Set Default Mailbox" → Select the edited profile → Tap "OK" → Tap "" to Exit